

Combination Type-F Across The Line Starter

THREE-PHASE with Control Power Transformer

- Branch Disconnect: Rotary through-the-door Handle
- Short-Circuit Protection: Manual Motor Protection
- Motor Control: Magnetic Contactor
- Overload Protection: Manual Motor Protection
- Control Devices: Hand-Off-Auto switch, Start-Stop pushbutton, control transformer
- Other enclosure options available upon request

ESWF Series - Combination Type-F Across The Line Starter with CPT

Max. 3-ph Hp Motors				Overload Setting Range (A)	Coil Voltage (Vac) ¹⁾	Metallic Enclosure Type 4/12		
200V	230V	460V	575V			Catalog Number	List Price	Box Size
-	-	1/2	1/2	0.63 - 1.0	480 / 120	ESWF-9T04N4-D05	\$1,525	F-1
1/4	1/3	3/4	1	1.0 - 1.6	240 / 120	ESWF-9T02N4-D06	\$1,525	F-1
					480 / 120	ESWF-9T04N4-D06		
1/2	1/2	1-1/2	1-1/2	1.6 - 2.5	240 / 120	ESWF-9T02N4-D07	\$1,525	F-1
					480 / 120	ESWF-9T04N4-D07		
3/4	1	2	3	2.5 - 4.0	240 / 120	ESWF-9T02N4-D08	\$1,525	F-1
					480 / 120	ESWF-9T04N4-D08		
1-1/2	1-1/2	3	5	4.0 - 6.3	240 / 120	ESWF-9T02N4-D09	\$1,525	F-1
					480 / 120	ESWF-9T04N4-D09		
3	3	5	7-1/2	6.3 - 10	240 / 120	ESWF-9T02N4-D10	\$1,525	F-1
					480 / 120	ESWF-9T04N4-D10		
5	5	10	15	10 - 16	240 / 120	ESWF-18T02N4-D11	\$1,610	F-1
					480 / 120	ESWF-18T04N4-D11		
7-1/2	7-1/2	15	15	16 - 20	240 / 120	ESWF-25T02N4-D12	\$1,715	F-1
					480 / 120	ESWF-25T04N4-D12		
10	10	20	25	25 - 32	240 / 120	ESWF-40T02N4-D14	\$1,865	F-2
					480 / 120	ESWF-40T04N4-D14		
10	15	25	30	32 - 40	240 / 120	ESWF-50T02N4-D19	\$2,290	F-3
					480 / 120	ESWF-50T04N4-D19		
15	15	30	40	40 - 50	240 / 120	ESWF-65T02N4-D20	\$2,440	F-3
					480 / 120	ESWF-65T04N4-D20		
20	20	40	60	50 - 65	240 / 120	ESWF-80T02N4-D21	\$2,540	F-3
					480 / 120	ESWF-80T04N4-D21		
20	25	50	60	55 - 75	240 / 120	ESWF-95T02N4-D22	\$2,700	F-3
					480 / 120	ESWF-95T04N4-D22		
25	30	60	75	70 - 90	240 / 120	ESWF-95T02N4-D23	\$2,840	F-3
					480 / 120	ESWF-95T04N4-D23		
30	30	75	100	80 - 100	240 / 120	ESWF-105T02N4-D24	\$3,030	F-3
					480 / 120	ESWF-105T04N4-D24		

Notes:

1) Please contact your local US for starters with other coil voltage.

- 3-phase starters can be wired for single-phase applications

Dimensions (inches)			
Box Size	Enclosure Size		
	H	W	D
F-1	12	12	8
F-2	16	16	8
F-3	20	20	12

